

MULTI-TECHNOLOGY TOUCHSCREEN READER

125 kHz, MIFARE® DESFIRE® EV2 & EV3, NFC



Available in keypad and standard versions



BENEFITS

- Compatible with legacy Prox 125 kHz technologies
- Seamless migration to secure technologies
- Customizable multi-function color touchscreen
- High-security function with scramble pad
- Modular concept for maximum cost optimization



- Display of your logo, images and customized text
- 2 configurable multicolor LEDs

The Architect® Hybrid reader facilitates your migrations to secure technologies. It combines identification technologies 125 kHz and 13.56 MHz with a customizable color touchscreen.

LECTEUR MULTI-TECHNOLOGIE

The Architect® Hybrid reader simplifies management of upgrades, technological migrations and complex multi-site configurations.

125 kHz Prox technologies

The reader is compatible with many legacy Prox technologies: EM®, Crosspoint®, Nedap®...

RFID MIFARE® DESFire® EV2 & EV3

It supports the latest contactless technologies with new data security features:

- **Secure Messaging EV2:** protection against attacks via interleaving and replay.
- **Proximity Check:** protection against relay attacks.

The reader supports the use of public security algorithms recognized by specialized and independent organizations in information security (ANSSI French cybersecurity agency and FIPS).

TOUCH KEYPAD READER

Both a reader and a tactile keypad, it allows user identification by combining the reading of an RFID card with the input of a personal keypad code.

The same reader can also operate in multiple mode. It authorizes, for example, the reading of cards for personnel and the entry of codes for visitors or temporary workers.

A CUSTOMIZED SCALABLE CONFIGURATION

The Architect® reader can be customized to meet your needs: all the features and security levels of the readers in your organization can be upgraded - by RFID credential or protocol.

The scalability allows you to remove the 125 kHz module once your technology migration is completed and / or to implement new functionality such as a touchscreen.

SMART FUNCTIONS



Scramble Pad: protects access against the fraudulent use of identification codes by the random display of the keys.



Mixed display: logo, instructions, personalized messages, images, or keypad are displayed by a simple touch wake-up of the screen.



Buttons 100% customizable using the SSCP® protocol: alarm activation, time management...



Doorbell: tactile button used to activate a doorbell via the relay built into the reader.

OPEN TECHNOLOGIES FOR EASY INTEGRATION

The reader is compatible with all access control systems and accepts multiple interfaces and protocols (Wiegand, Data / Clock, SSCP® and OSDPTM).

SPECIFICATIONS

Operating frequency / Standards	125 kHz 13.56 MHz: ISO14443 types A & B, ISO18092
Technology compatibilities	EM42xx / EM4x50, Crosspoint®, Nedap®, Format Wiegand 26, 34, 35 and 37 bits MIFARE® Ultralight® & Ultralight® C, MIFARE® Classic & Classic EV1, MIFARE Plus® (S/X) & Plus® EV1, MIFARE® DESFire® 256, EV1, EV2 & EV3, PicoPass® (CSN only), iCLASS™ (CSN only*)
Functions	CSN read-only, secure (file, sector) and secure protocol (Secure Plus) / Controlled by protocol (read/write)
Communication interfaces & protocols	TTL Data Clock (ISO2) or Wiegand output (encrypted option - S31) / RS485 output (encrypted option - S33) and RS232 output with secure SSCP® v1 and v2 communication protocols, OSDP™ v1 (plain communication) and v2 (SCP secure communication) Compatible with EasySecure interface
Touchscreen	Color touchscreen - 2.8" - 240 x 320 pixels 12 keys - Standard or random (scramble pad) keypad function / Functions: Card AND Key / Card OR Key Configurable by RFID card, UHF technology or software according to the interface
Reading distances**	Up to 6 cm / 2.36" with a 125 kHz card Up to 4 cm / 1.57" with a MIFARE DESFire® EV2 card
Light indicators	2 RGB LEDs - 360 colors ▲ ▲ ▲ Configuration by RFID card, software, external command (0V) or UHF technology according to the interface
Audio indicator	Internal buzzer Configuration by RFID card, software, external command (0V) or UHF technology according to the interface
Relay	Automatic tamper direction management or SSCP® / OSDP™ command according to the interface
Power requirement	230 mA / 12 VDC Max
Power supply	7 VDC to 28 VDC
Connections	10-pin plug-in connector (5 mm / 0.2") / 2-pin plug-in connector (5 mm / 0.2"): O/C contact - Tamper detection signal
Material	ABS-PC UL-V0 (black)
Dimensions (h x w x d)	156.4 x 80 x 30.5 mm / 6.14" x 3.15" x 1.2" (general tolerance following ISO NFT 58-000 standard)
Operating temperatures	- 20°C to + 70°C / - 4°F to + 158°F
Tamper switch	Accelerometer-based tamper detection system with key deletion option (patented solution) and/or message to the controller
Protection / Resistance	IP65 Level excluding connector - Weather-resistant with waterproof electronics (CEI NF EN 61086 homologation) Humidity: 0 - 95%
Mounting	Compatible with any surfaces and metal walls - Wall mount/Flush mount: - European 60 & 62 mm / 2.36" & 2.44" - American (metal/plastic) - 83.3 mm / 3.27" - Dimensions: 101.6 x 53.8 x 57.15 mm / 3.98" x 2.09" x 2.24" - Examples: Hubbel-Raco 674, Carlon B120A-UP
Certifications	CE (Europe), FCC (USA), IC (Canada) and UL
Part numbers	Secure read only - TTLARC-RX1-K/BF5-xx/1 Secure read only / Secure Plus - TTLARC-S31-K/BF5-xx/1 Secure read only - RS232ARC-RX2-K/BF5-5AB/1 Secure read only - RS485ARC-RX3-K/BF5-7AB/1 Secure read only / EasySecure interface - RS485ARC-RX3-K/BF5-7AA/1 Secure read only / Secure Plus - RS485ARC-S33-K/BF5-7AB/1 Secure read only / Secure Plus / EasySecure interface - RS485ARC-S33-K/BF5-7AA/1 Controlled by SSCP® v1 protocol - RS232ARC-W32-K/BF5-5AA/1 Controlled by SSCP® v1 protocol - RS485ARC-W33-K/BF5-7AA/1 Controlled by SSCP® v2 protocol - RS485ARC-W33-K/BF5-7AD/1 Controlled by OSDP™ v1 & v2 protocol - RS485ARC-W33-K/BF5-7OS/1

DISCOVER THE COMPANION PRODUCTS



13.56 MHz or dual frequency
ISO cards & key holders



NFC smartphones
using STid Mobile ID® application



Privacy filter
ANTI-SPY-ARC



SECARD
SECard configuration kit and
SSCP® v1 & v2 and OSDP™ protocols

*Our readers only read the iCLASS™ chip serial number / UID PICO1444-3B. They do not read iCLASS™ cryptographic protection or the HID Global serial number / UID PICO 15693.

**Caution: information about the distance of communication: measured from the center of the antenna, depending on the type of credential, size of the credential, operating environment of the reader, temperatures, power supply voltage and reading functions (secure reading). External interference may reduce reading distances.

Legal: STid, STid Mobile ID® and Architect® are registered trademarks of STid SAS. All trademarks mentioned in this document belong to their respective owners. All rights reserved – This document is the property of STid. STid reserves the right to make changes to this document and to cease marketing its products and services at any time and without notice. Photos are not contractually binding.

Headquarters / EMEA

13850 Créasque, France
Tel.: +33 (0)4 42 12 60 60

PARIS-IDF

92290 Châtenay-Malabry, France
Tel.: +33 (0)1 43 50 11 43

STid UK Ltd.

Gallows Hill, Warwick CV34 6UW, UK
Tel.: +44 (0) 192 621 7884

NORTH AMERICA

Irving, Texas 75063-2670, USA
Tel.: +1 469 524 3442

LATINO AMERICA

San Rafael 06470 CDMX, México
Tel.: +52 (55) 5256 4706

info@stid.com

www.stid-security.com